



Signalgenerator and Frequency-Counter



Technical Specifications

Article No.	JT-JDS6600
Features	2 Channel Signalgenerator Signal-Forms: Sine, square, triangle, pulse, half-wave, noise, Lorenz pulse, exponential rise/fall, CMOS and more 1 Channel Frequency-Counter
Frequency-Range (Sine)	0 - 60MHz
Frequency-Range (Square, Triangle)	0 - 15MHz
Frequency-Range (PWM, CMOS, TTL, Arbitrary)	0 - 6MHz
Min. Frequency Resolution	0,01 μ Hz
Frequency Accuaracy	+/-20ppm
Frequency Stability	+/-1ppm/3h
Display Mode	TFT LCD Color display
Display Size	2,4"
Operating temperature and humidity	Temperature: 0 - 40°C / Humidity: <80%
Dimensions	194 x 178 x 69mm
Scope of Delivery	Signalgenerator, 2x BNC Signal terminals, power supply
EAN	4250236817811