
February 1995

_M710 Voltage Comparator




LM710 Voltage Comparator

General Description

The LM710 series are high-speed voltage comparators intended for use as an accurate, low-level digital level sensor or as a replacement for operational amplifiers in comparator applications where speed is of prime importance. The circuit has a differential input and a single-ended output, with saturated output levels compatible with practically all types of integrated logic.

The device is built on a single silicon chip which insures low offset and thermal drift. The use of a minimum number of stages along with minority-carrier lifetime control (gold doping) makes the circuit much faster than operational amplifiers in saturating comparator applications. In fact, the low stray and wiring capacitances that can be realized with monolithic construction make the device difficult to duplicate with discrete components operating at equivalent power levels.

The LM710 series are useful as pulse height discriminators, voltage comparators in high-speed A/D converters or go, no-go detectors in automatic test equipment. They also have applications in digital systems as an adjustable-threshold line receiver or an interface between logic types. In addition, the low cost of the units suggests them for applications replacing relatively simple discrete component circuitry.



© 1995 National Semiconductor Corporation TL/H/10410

RRD-B30M115/Printed in U. S. A.

Absolute Maximum Ratings

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications. Positive Supply Voltage +14V

Positive Supply Voltage	+14V
Negative Supply Voltage	-7V
Peak Output Current	10 mA
Output Short Circuit Duration	10 seconds
Differential Input Voltage	$\pm 5V$
Input Voltage	$\pm 7V$

Power Dissipation TO-99 (Note 1) Plastic Dual-In-Line Package (Note 2)	700 mW 950 mW
Operating Temperature Range LM710 LM710C	-55°C to +125°C 0°C to +70°C
Storage Temperature Range	-65°C to +150°C
Lead Temperature (Soldering, 10 sec.)	260°C

Electrical Characteristics (Note 3)

Parameter	Conditions	LM710			LM710C			Units
rarameter	Conditions	Min Typ		Мах	Min	Тур	Max	Units
Input Offset Voltage	$R_{S} \leq 200 \Omega, V_{CM} = 0V, T_{A} = 25^{\circ}C$		0.6	2.0		1.6	5.0	mV
Input Offset Current	$V_{OUT} = 1.4V, T_A = 25^{\circ}C$		0.75	3.0		1.8	5.0	μΑ
Input Bias Current	$T_A = 25^{\circ}C$		13	20		16	25	μA
Voltage Gain	$T_A = 25^{\circ}C$	1250	1700		1000	1500		
Output Resistance	$T_A = 25^{\circ}C$		200			200		Ω
Output Sink Current	$ \begin{array}{l} V_{OUT}=0, T_A=25^\circ C\\ \Delta V_{IN}\geq 5\mbox{ mV}\\ \Delta V_{IN}\geq 10\mbox{ mV} \end{array} $	2.0	2.5		1.6	2.5		mA mA
Response Time	T _A = 25°C (Note 4)		40			40		ns
Input Offset Voltage	$R_{S} \leq 200 \Omega, V_{CM} = 0V$			3.0			6.5	mV
Average Temperature Coefficient of Input Offset Voltage	$\begin{array}{l} T_{MIN} \leq T_A \leq T_{MAX} \\ R_S \leq 50\Omega \end{array}$		3.0	10		5.0	20	μV/°(
Input Offset Current	$ \begin{array}{l} T_{A} = T_{A} \underset{MAX}{MAX} \\ T_{A} = T_{A} \underset{MIN}{MIN} \end{array} $		0.25 1.8	3.0 7.0			7.5 7.5	μΑ μΑ
Average Temperature Coefficient of Input Offset Current	$\begin{array}{l} 25^{\circ}C \leq T_{A} \leq T_{MAX} \\ T_{MIN} \leq T_{A} \leq 25^{\circ}C \end{array}$		5.0 15	25 75		15 24	50 100	nA/°(nA/°(
Input Bias Current	$T_A = T_{MIN}$		27	45		25	40	μA
Input Voltage Range	$V^- = -7V$	±5.0			±5.0			V
Common-Mode Rejection Ratio	$R_{S} \le 200 \Omega$	80	100		70	98		dB
Differential Input Voltage Range		±5.0			±5.0			V
Voltage Gain		1000			800			V/V
Positive Output Level	$\begin{array}{l} -5 \text{ mA} \leq I_{OUT} \leq 0 \\ V_{IN} \geq 5 \text{ mV} \\ V_{IN} \geq 10 \text{ mV} \end{array}$	2.5	3.2	4.0	2.5	3.2	4.0	V V
Negative Output Level	$\begin{array}{l} V_{IN} \geq 5 \; mV \\ V_{IN} \geq 10 \; mV \end{array} \label{eq:VIN}$	-1.0	-0.5	0	-1.0	-0.5	0	V V
Output Sink Current	$\label{eq:VIN} \begin{split} V_{IN} &\geq 5 \text{ mV}, V_{OUT} = 0 \\ T_A &= 125^\circ\text{C} \\ T_A &= -55^\circ\text{C} \end{split}$	0.5 1.0	1.7 2.3					mA mA
	$\label{eq:VIN} \begin{array}{l} V_{\text{IN}} \geq 10 \text{ mV}, V_{\text{OUT}} = 0 \\ 0^{\circ}\text{C} \leq T_{\text{A}} \leq +70^{\circ}\text{C} \end{array}$				0.5			mA

Parameter	Conditions -	LM710				Units		
		Min	Тур	Max	Min	Тур	Мах	Clints
Positive Supply Current	$V_{IN} \ge 5 \text{ mV}$		5.2	9.0				mA
	$V_{IN} \ge 10 \text{ mV}$					5.2	9.0	mA
Negative Supply Current	$V_{IN} \ge 5 \text{ mV}$		4.6	7.0				mA
	$V_{\text{IN}} \geq 10 \text{ mV}$					4.6	7.0	mA
Power Consumption	$I_{OUT} = 0$							
-	$V_{IN} \ge 5 \text{ mV}$		90	150				mW
	$V_{IN} \ge 10 \text{ mV}$						150	mW


Note 1: Rating applies for ambient temperatures of 25°C; derate linearly at 5.6 mW/°C for ambient temperatures above 25°C.


Note 2: Derate linearly at 9.5 mW/°C for ambient temperatures above 25°C.

Note 3: These specifications appy for V⁺ = 12V, V⁻ = $-6V_{r}$, $-55^{\circ}C \le T_{A} \le +125^{\circ}C$ for LM710 and $0^{\circ}C \le T_{A} \le +70^{\circ}C$ for LM710C unless otherwise specified: The input offset voltage and input offset current (see definitions) are specified for a logic threshold voltage of 1.8V at $-55^{\circ}C$, 1.4V at 25°C, and 1V at 125°C for LM710 and 1.5V at 0°C, 1.4V at 25°C, and 1.2V at 70°C for LM710C.


Note 4: The response time specified (see definitions) is for a 100 mV input step with 5 mV overdrive (LM710) or a 10 mV overdrive (LM710C).

Typical Applications








Level Detector with Lamp Driver




TL/H/10410-7











National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.