

Type: ASK/OOK Super-Heterodyne Receiver Module Model: RXB18-XXX

1. DESCRIPTION:

RXB18 is an ASK/OOK receiver super-heterodyne module, which is designed specifically for unlicensed remote-control and wireless security receiver operating at 315/433.92MHz under FCC Part 15 regulation or pass ETSI certification. The RXB18 is based on a single-conversion, super-heterodyne receiver architecture and incorporates an entire Phase-Locked Loop (PLL) for precise local oscillator generation. It can be used in OOK/ HCS/ PWM modulation signal and demodulate to digital signal.

RXB18 is a high performance module at a competitive cost and easily to design for your product. The RXB18 module can be also a RoHS compliance product.



2. FEATURES:

- Frequency: 315M/433.92MHz (custom frequency is available)
- Low cost ASK/OOK radio superhet receiver
- High frequency stability (no adjust components) & coherence
- Very low RF re-radiation at the antenna
- Operation temperature: -20° C \sim 70 $^{\circ}$ C (It can custom to $-40 \sim 85^{\circ}$ C upon requests)
- Supply voltage: 3.6~5.5V
- Available frequency: 315/433.92MHz (other Frequency customer selectable)
- Compatible with most (ASK/OOK) transmitters



3. APPLICATION:

- Smart home system
- Remote controls
- Remote fan and light control
- Garage door and gate openers
- Alarm and security system





1. ANT 2. GND 3. GND 4. VCC 5. VCC 6. DO 7. DO 8. GND

Figure1 RXB38 Shape & Pins

Pin Name	Pin Definition				
ANT	RF signal input pin, connect antenna outside(Note1)				
GND	Connect to negative power supply				
GND	Connect to negative power supply				
VDD	Connect to positive power supply				
VDD	Connect to positive power supply				
DATA	Data output pin, connect to MCU or decoder's input pin				
DATA	Data output pin, connect to MCU or decoder's input pin				
GND	Connect to negative power supply				

Note1: ANT pin is a 50 ohm antenna input. The length is about: 23cm for 315MHz 17cm for 433.92MHz

SHENZHEN JMRTH TECH. CO., LTD Tel: 0755-88351194 web: http://www.jmrth.com



5. ELECTRICAL CHARACTERISTICS

Baramotor	Specification			Lloit	Condition
Falalletei	Min	Тур	Max	Unit	Condition
Frequency range		315/433.92		MHz	
Receiver sensitivity		-110		dBm	
Data rata	0.58	1.2	2.4	Kbaud	
Supply voltage, VDD	3.6		5.5	V	DC
Current	4.8		7	mA	
Operation temperature	-20		+70	°C	

6. MECHANICAL SIZE: (UNIT: mm)



